







Fenix PD35 2014 EDITION Flashlight

Are compact size and mighty output really mutually exclusive? Not in the case of PD35. Weighting only 87 grams and less than 14 centimeters long, PD35 delivers a stunning 960-lumen maximum output from one 18650 battery. Six outputs including strobe mode cover from daily use to outdoor and professional use while a simple press on the side switch is all you need to select output. Portable becomes powerful with this go-everywhere, category-changing model from Fenix.

Technical Parameters

ANSI/NEMA FL1	General Mode					Strobe
	Turbo	High	Mid	Low	Eco	
 OUTPUT	960 Lumens*	460 Lumens	180 Lumens	50 Lumens	14 Lumens	960 Lumens
 RUNTIME	1h10min* *	3h 15min***	10h	38h	150h	
 DISTANCE	208m□Max□					
 INTENSITY	10800cd□Max□					
 IMPACT RESISTANT	1m					
 WATERPROOF	IPX-8□underwater 2m					
EXTRA FUNCTION						
ACCESSORIES	Holster, clip, lanyard and two spare O-rings					

Notice: The above-mentioned parameters (lab-tested by Fenix using ARB-L2S rechargeable Li-ion battery) are approximate and may vary between flashlights, batteries and environments.

*The flashlight will drop down into the high brightness level after working about 5 minutes in the Turbo mode. Therefore, the runtime of Turbo output is an accumulated time.

** When powered by two CR123A batteries, the Turbo output will be around 1000 lumens for the first couple of minutes.

***The flashlight will transfer into the Mid brightness level after working about 30 minutes in the High mode. Therefore, the runtime of High output is an accumulated time.

- ⊙ Cree XM-L 2 (U2) LED with a lifespan of 50,000 hours
- ⊙ Uses one 18650 rechargeable Li-ion battery or two 3V CR123A Lithium batteries
- ⊙ 139mm (Length) x 25.4mm (Diameter)
- ⊙ 87-gram weight (excluding the battery)
- ⊙ Digitally regulated output - maintains constant brightness
- ⊙ Low-voltage warning function to remind you to replace the battery
- ⊙ Reverse polarity protection guards against improper battery installation
- ⊙ Over-heat protection to avoid high-temperature of the surface
- ⊙ Anti-roll, slip-resistant body design
- ⊙ Tactical tail switch with momentary-on function
- ⊙ Side switch on the head
- ⊙ Made of durable aircraft-grade aluminum
- ⊙ Premium Type III hard-anodized anti-abrasive finish
- ⊙ Toughened ultra-clear glass lens with anti-reflective coating

Operation Instruction

On/Off Operation:

Press the tail switch gently for momentary lighting or until it clicks to activate and lock the PD35. Press again to turn the light off.

Mode Selecting:

With the light on, press the side switch to cycle through five different brightness levels from Turbo → Eco → Low → Medium → High.

Strobe

Press and hold the side switch for 1 second to enter into Strobe mode.

A single press on the side switch will return the flashlight to general lighting mode from Strobe.

Intelligent Memory Circuit

The Fenix PD35 memorizes the last brightness level used in the general mode, but it will not remember the Strobe modes. The next time you turn the flashlight on, it will activate the last brightness level you selected.

Turbo Output

In Turbo output, the LED runs at the highest brightness and discharge rate. Use of high

quality batteries is recommended for peak performance. As a high-performance light, the PD35 accumulates significant heat while at Turbo output. To protect the light and user, the PD35 automatically drops down into the High brightness level after running at Turbo output for about five minutes. If further Turbo output is needed, reset the light with the side switch. Be advised that prolonged Turbo output may reduce the PD35's life span or cause permanent damage to the light.

High Output

To protect the light and user, the PD35 automatically drops into the Mid brightness level after working in High output for about 30 minutes. If further High output is needed, reset the light with the side switch.

Low-voltage Warning Function

When the voltage level drops below the preset level, the PD35 is programmed to downshift to a lower brightness level. When this happens in Eco output mode, the flashlight blinks three times every five minutes to remind you to replace the battery.

Battery Specifications

Type	Dimensions	Nominal Voltage	Usability	
Fenix ARB-L2/L2M/L2S/L2P	18650	3.6V/3.7V	Recommended	√
Non-rechargeable Battery (Lithium)	CR123A	3V	Usable	√
Rechargeable Battery (Li-ion)	16340	3.6V/3.7V	Cautious*	!
Rechargeable Battery (Li-ion)	18650	3.6V/3.7V	Cautious*	!
Rechargeable Battery □LiFePO ₄ □	16340	3.2V	Usable	√
Rechargeable Battery □LiFePO ₄ □	18650	3.2V	Banned	✘

Warning: Please do not mix batteries of different brands, size, capacity or type. Doing so may cause damage to the flashlight or the batteries being used.

*18650 /16340 Li-ion batteries are powerful cells designed for commercial applications and must be treated with caution and handled with care. Quality batteries with circuit protection will reduce the potential risk for combustion or explosion but cell damage or short circuiting are potential risks the user assumes.

Battery Replacement

Unscrew the tail cap to insert the batteries with the anode side (+) toward the light's

head, screw the tail cap back on.

Usage and Maintenance

ⓄPlease don't disassemble the sealed head, doing so can cause damage to the flashlight and will void the warranty.

ⓄWe recommend the use of high quality battery. If the flashlight is not to be used for an extended period, remove the battery, or the flashlight could be damaged by electrolyte leakage or battery explosion.

ⓄDue to the momentary-on tactical switch, the flashlight may be accidentally activated when stored, transported or placed in a pocket. Unscrew the tail cap one-half turn or take out the battery to avoid unwanted operation.

ⓄThe O-ring may be worn out after using for a long time. If this happens, please replace the O-ring with a new one to keep the flashlight properly sealed against water.

ⓄPlease clean the contacts of your light from time to time, especially if the light flickers or doesn't light up. There may be several reasons for a flickering or not working light:

Reason A: The battery needs replacing.

Solution: Replace the battery (Please confirm the correct orientation of positive and negative ends).

Reason B: The threads, PCB board contact or other contacts are dirty.

Solution: Clean the contact points with an alcohol soaked cotton swab.

If the above methods don't work, please refer to the warranty policy.

Notice: The routine cleaning video can be watched and downloaded through Fenix official website, please click the service channel->"maintenance for light".

Product Warranty

We will replace products with manufacturing defects within 15 days of purchase and repair a light free of charge within 24 months of purchase if problems develop with normal use; if repair is required after 24 months from the date of purchase, we will charge for parts. The total repair fee is dictated by the cost of the replaced materials.

Product Registration

We kindly suggest that you register your product on the official website of Fenixlight Limited (www.fenixlight.com). You'll receive an extra six months of warranty coverage once you have successfully registered. By participating in an optional customer survey, you are entered in a drawing for free Fenix products.

Warning

PD35 is a high-intensity lighting device capable of causing eye damage. Avoid shining the light directly into anyone's eyes.

Available Accessories

Type	Model	Description	Note
Transparent diffuser tip	AOD-S		
Traffic wand	AOT-M		
Remote pressure switch	AR102		
Bike mount	ALB-10		
Belt clip	AB02		

FENIXLIGHT LIMITED

Tel: +86-755-29631163/83/93 Fax: +86-755-29631181

<http://www.fenixlight.com>

E-mail: info@fenixlight.com

Address: 8/F, 2nd Building, Dong Fang Ming

Industrial Center, 33rd District, Bao' an,

Shenzhen 518133, China