







## PD30 Flashlight

Fenix PD30 is a multifunctional flashlight of high intensity; it offers 257 Lumens beam with a compact size. Meanwhile, it perfectly combines the high brightness and long runtime with 4 levels of brightness and 2 types of flashing mode. With Fenix advanced technology to keep constant brightness, and waterproofing to IPX-8 standard with its reliable structure, PD30 is a perfect solution for your outdoor illumination or emergency use.

### Technical Parameters

ANSI/FSC	Turbo Mode		General Mode			
	Turbo	Strobe	Low	Mid	High	SOS
 OUTPUT	257 LUMENS	257 LUMENS	10 LUMENS	67 LUMENS	124 LUMENS	124 LUMENS
 RUNTIME	2h 37min		126h	17h	7h 45min	
 DISTANCE	127m					
 INTENSITY	4038cd					
 IMPACT RESISTANT	1.5m					
 WATERPROOF	IPX-8, underwater 2m					
EXTRA FUNCTION						
ACCESSORIES	holster, lanyard, body clip, two spare o-rings, and a rubber switch boot					

- ◎ Cree XP-G LED (R5) with a lifespan of 50,000 hours
- ◎ Uses two 3V CR123A batteries (Lithium)
- ◎ 118mm (Length) x 21.5mm (Diameter)
- ◎ 53-gram weight (excluding batteries)
- ◎ Digitally regulated output - maintains constant brightness
- ◎ Patented physical structure avoids circuit damaging from reverse connection of battery

- ◎ Anti-roll, slip-resistant body design
- ◎ Capable of standing up securely on a flat surface to serve as a candle
- ◎ Made of durable aircraft-grade aluminum
- ◎ Premium Type III hard-anodized anti-abrasive finish
- ◎ Toughened ultra-clear glass lens with anti-reflective coating

Notice: The above-mentioned parameters (tested by high-quality CR123A Lithium battery in Lab) are approximate and may vary between flashlights, batteries, and environments.

## **Operation Instruction**

Fully press (click) to switch on and turn the bezel to select the General Mode or the Turbo Mode. A soft-press (no click) anytime while the light is on will change the brightness levels of a certain mode. Keep the light off for over 2 seconds and the light will turn completely off, restoring the regulation circuit to the default setting.

## **Battery Replacement**

Unscrew the tail cap to insert the batteries with the anode side (+) toward the light's head, screw the tail cap to test.

## **Usage and Maintenance**

- ◎ Please don't disassemble the sealed head, doing so can cause damage to the flashlight and will void the warranty.
- ◎ Please use battery of high quality, and take out the battery if the flashlight will not be used for a long time, or it may cause damage from electrolyte leakage or battery explosion.
- ◎ The O-ring may be worn out after using for a long time. If it happens, please replace the O-ring with a new one to keep the flashlight properly sealed against water.
- ◎ Please clean the contacts of your light from time to time, especially if the light flickers or doesn't light up. There may be several reasons for a flickering or not working light:

Reason A: The battery needs replacing.

Solution: Replace batteries (Please confirm the correct installation of anode and cathode).

Reason B: The threads, PCB board contact or other contacts are dirty.

Solution: Clean the contact points with an alcohol soaked cotton swab.

If the above methods don't work, please contact the distributors and refer to the warranty policy.

## **Product Warranty**

We will replace products afflicted with manufacturing defects within 15 days of purchase and repair a light free of charge within 24 months of purchase if problems develop with normal use; if repair is required after 24 months from the date of purchase, we will charge for parts. The total repair fee is dictated by the cost of the replaced materials.

## **Warranty Card Registration**

We kindly suggest that you register your guarantee card on the official website for Fenixlight Limited. You can get an extra six-month warranty period once you have successfully registered. What's more, you could take part in the lottery of questionnaire at the same time.

## **Warning**

PD30 is a high intensity lighting device and capable of causing eye damage, avoid shining the light directly into the eyes.

Avoid the use of 16340 rechargeable Lithium batteries or damage will be caused to the light circuit.

FENIXLIGHT LIMITED

Tel: +86-755-29631163/83/93 Fax: +86-755-29631181

<http://www.fenixlight.com>

E-mail: [info@fenixlight.com](mailto:info@fenixlight.com)

Address: 8/F, 2nd Building, Dong Fang Ming

Industrial Center, 33rd District, Bao' an,

Shenzhen 518133, China