







Fenix E25 Flashlight

The Fenix E25 delivers 260 lumen Burst output along with three other brightness levels controlled by a single all-function switch. Two readily-available AA batteries power the E25 with up to 72 hours runtime on low mode.

Technical Parameters

ANSI/NEMA FL1		General Mode			Burst
		High	Mid	Low	
 OUTPUT		130 Lumens	55 Lumens	8 Lumens	260 Lumens
 RUNTIME	Ni-MH Battery	3h 30mini	10h	72h	/
	Alkaline Battery	1h 45min	8h15min	72h	
 DISTANCE		180m Max			
 INTENSITY		8100cd Max			
 IMPACT RESISTANT		1m			
 WATERPROOF		IPX-8 underwater 2m			
ACCESSORIES		Lanyard, spare O-ring			

Notice: The above-mentioned parameters (lab tested by Fenix using 2500mAh Ni-MH battery and the included Alkaline battery) are approximate and may vary between flashlights, batteries and environments.

© Cree XP-E2 LED with a lifespan of 50,000 hours

© Uses two AA batteries

© 146mm (Length) x 24mm (Diameter)

- ⊙ 73-gram weight (excluding batteries)
- ⊙ Digitally regulated output - maintains constant brightness
- ⊙ Reverse polarity protection guards against improper battery installation
- ⊙ All-function switch, simple and convenient operation
- ⊙ Capable of standing up securely on a flat surface to serve as a candle
- ⊙ Made of durable aircraft-grade aluminum
- ⊙ Premium Type III hard-anodized anti-abrasive finish
- ⊙ Toughened ultra-clear glass lens with anti-reflective coating

Operation Instruction

ON/OFF

Press and hold the switch for 0.5 seconds to turn the light on or off.

Output Selection

With the light on, press the switch to select the brightness level in the order of High → Mid → Low.

Burst Mode

Press and hold the side switch for one second to activate the Burst mode even if the light is off. When the switch is released, the light will return to the previous condition.

Intelligent Memory Circuit

The light remembers the last used brightness level when the light is turned off and then on again.

Battery Specifications

Type	Dimensions	Nominal Voltage	Usability	
Ni-MH Battery	AA	1.2V Recommended	√	
Alkaline Battery	AA	1.5V	Usable	√
Non-rechargeable Battery (Lithium)	AA	1.5V	Usable	√
Rechargeable Battery (Li-ion)	14500	3.7V	Banned	×

Warning: Please do not mix batteries of different brands, size, capacity or type. Doing so may cause damage to the flashlight or the batteries being used.

Battery Replacement

Unscrew the light head to insert the batteries with the anode side (+) toward the light head, screw the light head back on to test.

Usage and Maintenance

Ⓞ Please don't disassemble the sealed, as doing so can cause damage to the flashlight and will void the warranty.

Ⓞ Use only recommended high performance batteries with this high discharge light: A Ni-MH rechargeable cell is recommended as alkaline batteries will reduce the flashlight's runtime.

Ⓞ We recommend the use of high quality battery. If the flashlight is not to be used for an extended period, remove the battery, or the flashlight could be damaged by electrolyte leakage or battery explosion.

Ⓞ Unscrew the tail cap one-half turn or take out the battery to prevent accidental activation during storage or transport.

Ⓞ The O-ring may be worn out after using for a long time. If it happens, please replace the O-ring with a new one to keep the flashlight properly sealed against water.

Ⓞ Please clean the contacts of your light from time to time, especially if the light flickers or doesn't light up. There may be several reasons for a flickering or not working light:

Reason A: The batteries need replacing.

Solution: Replace the batteries (Please confirm the correct installation of anode and cathode).

Reason B: The threads, PCB board contact or other contacts are dirty.

Solution: Clean the contact points with an alcohol soaked cotton swab.

If the above methods don't work, please contact the distributors and refer to the warranty policy.

Product Warranty

We will replace products afflicted with manufacturing defects within 15 days of purchase and repair a light free of charge within 24 months of purchase if problems develop with normal use; if repair is required after 24 months from the date of purchase, we will charge for parts. The total repair fee is dictated by the cost of the replaced materials.

Product Registration

We kindly suggest that you register your product on the official website for Fenixlight Limited (www.fenixlight.com). You can get an extra six-month warranty period once you have successfully registered. By participating in an optional customer survey, you are entered in a drawing for free Fenix products.

Warning

E25 is a high-intensity lighting device capable of causing eye damage. Avoid shining the light directly into the eye.

FENIXLIGHT LIMITED

Tel: +86-755-29631163/83/93 Fax: +86-755-29631181

www.fenixlight.com

E-mail: info@fenixlight.com

Address: 8/F, 2nd Building, Dong Fang Ming
Industrial Center, 33rd District, Bao' an,
Shenzhen 518133, China